

PREMIUM


CZUJNIKI RUCHU / MOTION SENSORS

LX01



- detektor ruchu z dwoma zakresami regulacji: czas działania i natężenie oświetlenia,
- kąt / zasięg detekcji: 160 stopni / max. 9 m (<24°C),
- obciążenie: 1-800 W (dla źródeł żarowych), 1-400 W (dla źródeł ledowych i świetlówek kompaktowych),
- czas pracy: min. 10 s ±3 s, max. 7 min ±2 min,
- zakres natężenia światła: 10-2000 lux,
- wykrywana prędkość ruchu: 0,6-1,5 m/s,
- pobór mocy: 0,50 W (podczas pracy), 0,1 W (w trybie czuwania),
- optymalna wysokość do instalacji: 1-1,8 m.

- motion sensor with two adjustable settings: operating time and light intensity,
- detection angle/range: 160 degrees / max. 9 m (<24°C),
- load capacity: 1-800 W (for incandescent light sources), 1-400 W (for LED and compact fluorescent lamps),
- operating time: min. 10 s ±3 s, max. 7 min ±2 min,
- light intensity range: 10-2000 lux,
- detected motion speed: 0,6-1,5 m/s,
- power consumption: 0,50 W (while working), 0,1 W (in standby mode),
- recommended installation height: 1-1,8 m.



MODEL	INDEKS	KOLOR	WAGA NETTO [kg]	PAKOWANIE [szt.]	KOD EAN
MODEL	INDEX	COLOR	NET WEIGHT [kg]	PACKING [pcs]	BARCODE
LX01	KVLX01140ST	BIAŁY WHITE	0,09	100	5900605090589

