

PREMIUM


CZUJNIKI RUCHU / MOTION SENSORS

LX41



- detektor ruchu z dwoma zakresami regulacji: czas działania i natężenie oświetlenia,
- kąt / zasięg detekcji: 360 stopni / max. 6 m (<24°C),
- obciążenie: 1-1200 W (dla źródeł żarowych), 1-300 W (dla źródeł ledowych i świetlówek kompaktowych)
- czas pracy: min. 10 s ±3 s, max. 8 min ±2 min,
- zakres natężenia światła: 3-2000 lux,
- wykrywana prędkość ruchu: 0,6-1,5 m/s,
- pobór mocy: 0,5 W (podczas pracy), 0,1 W (w trybie czuwania),
- optymalna wysokość do instalacji: 2,2-4 m.

- motion sensor with two adjustable settings: operating time and light intensity,
- detection angle/range: 360 degrees / max. 6 m (<24°C),
- load capacity: 1-1200 W (for incandescent light sources), 1-300 W (for LED and compact fluorescent lamps),
- operating time: min. 10 s ±3 s, max. 8 min ±2 min,
- light intensity range: 3-2000 lux,
- detected motion speed: 0.6-1.5 m/s,
- power consumption: 0.5 W (while working), 0.1 W (in standby mode),
- recommended installation height: 2.2-4 m.



MODEL	INDEKS	KOLOR	WAGA NETTO [kg]	PAKOWANIE [szt.]	KOD EAN
MODEL	INDEX	COLOR	NET WEIGHT [kg]	PACKING [pcs]	BARCODE
LX41	KVLX41360STB	BIAŁY WHITE	0,07	50	5900605091531

